

5" modero widescreen touch panel



EXPECT NOTHING LESS

Using a smaller touch panel shouldn't mean you have to sacrifice the range of multimedia features you get with larger models. The 5" Modero Widescreen offers what no other panel of its size on the market can — audio/video-ready capabilities, a 16x9 widescreen user interface and the unique AMX Modero design all rolled into an unbelievably sleek Wall/Flush Mount display.

PERFECTLY DISCREET.

The 5" Modero Widescreen fits discreetly on the wall, making it the perfect solution for smaller wall spaces. In the home, for example, it offers just the right amount of control in the foyer, hallways, kitchen, bedroom and bathroom. A popular solution in education and corporate settings, this panel provides convenient and seamless one-touch control from the entryways into offices, at the head of meeting rooms, and in lecterns and podiums. In fact, you'll hardly know it's there thanks to the panel's ultra-slim bezel design.

PREPARE TO FLIP OUT

Literally. Feel free to position the 5" Modero Widescreen with programmable pushbuttons located across the top or bottom of the bezel. It simply depends on how you prefer to view and take control of the user interface. A unique AMX feature "flips" the text, icons and video windows as needed, so no matter which way you choose to display the panel — pushbuttons up or pushbuttons down — everything appears on-screen as it should.



5" modero widescreen touch panel

NXD-CV5 TOUCH PANELS (FG2261)

LCD

5" Color active-matrix LCD 16x9 (800 x 480 pixel resolution)

Brightness: 170+ cd/m²

Contrast: 250:1

Viewing Angle: left/right 45°, down 30°, up 15°

Display colors: 256K (18-bit color depth)

Active Viewing Area: 152.4 mm x 91.44 mm

POWER

1.0 Amps @ 12.0 VDC (wired)

MEMORY

64B Extended Memory Module

64MB Compact Flash

DIMENSIONS (HWD)

TBD

ENCLOSURES

ABS Polycarbonate enclosure in black matte finish with platinum color bezel trim

FRONT PANEL

Light Sensor: Photosensitive light detector for automatic adjustment of the panel brightness

Motion Sensor (PIR): Proximity Infrared Detector to wake the panel when the panel is approached

Front Setup Access Button: Pushbutton (grey) used to either put the panel into a "sleep" or "wake" state and/or access the Setup and Calibration pages

Speakers: 2 - Frequency response 450 Hz - 7 KHz

Microphone: Used for audio/intercom applications

OPTIONAL ACCESSORIES

PSN4.4 Power Supply (13.5 VDC) with 3.5 mm Phoenix connector (FG423-45)

Optional Rackmount kit for 5" Wallmount Panels

Optional Conduit Box for 5" Wallmount Panels

Optional NXA-AVB/Ethernet Breakout Box

WEIGHT

TBD



IT'S YOUR WORLD. TAKE CONTROL.

ARGENTINA • AUSTRALIA • BELGIUM • BRAZIL • CANADA • CHINA • ENGLAND • FRANCE • GERMANY • GREECE • HONG KONG • INDIA • INDONESIA • ITALY • JAPAN
LEBANON • MALAYSIA • MEXICO • NETHERLANDS • NEW ZEALAND • PHILIPPINES • PORTUGAL • RUSSIA • SINGAPORE • SPAIN • SWITZERLAND • THAILAND • TURKEY • USA
ATLANTA • BOSTON • CHICAGO • CLEVELAND • DALLAS • DENVER • INDIANAPOLIS • LOS ANGELES • MINNEAPOLIS • PHILADELPHIA • PHOENIX • PORTLAND • SPOKANE • TAMPA
3000 RESEARCH DRIVE, RICHARDSON, TX 75082 • 800.222.0193 • 469.624.8000 • +1.469.624.7400 • 469.624.7153 fax • www.amx.com